



Oxford Cambridge and RSA

AS Level Computer Science

H046/01 Computing principles

Sample Question Paper

Date – Morning/Afternoon

Time allowed: 1 hour 15 minutes



Do not use:

- a calculator



First name										
Last name										
Centre number						Candidate number				

INSTRUCTIONS

- Use black ink.
- Complete the boxes above with your name, centre number and candidate number.
- Answer **all** the questions.
- Write your answer to each question in the space provided.
- Additional paper may be used if required but you must clearly show your candidate number, centre number and question number(s).
- Do **not** write in the bar codes.

INFORMATION

- The total mark for this paper is **70**.
- The marks for each question are shown in brackets [].
- Quality of extended responses will be assessed in questions marked with an asterisk (*).
- This document consists of **16** pages.

Answer **all** questions.

- 1 Intensive Care Units in hospitals are for patients in need of round the clock monitoring and support. Computerised systems can be used to monitor patients' vital signs (temperature, heart rate, blood pressure and breathing). They can then alert medical professionals to any significant changes.

These systems usually run on an embedded, real-time, operating system.

- (a) (i) State what is meant by the term *real-time*.

.....
.....[1]

- (ii) Explain why a real-time operating system would be suitable for this purpose.

.....
.....
.....[2]

- (b) (i) Explain two advantages of this monitoring system having its operating system stored in ROM.

.....
.....
.....[2]

- (ii) The monitoring system also has RAM. Describe what happens to the contents of RAM and ROM when power to the monitoring system is removed.

.....
.....
.....[2]

2 InterMovie is a service that allows users to stream movies over the Internet.

(a) When users have played a movie it remains stored in a cache on the user's computer. This means that someone wanting to access the same film in future can stream it from other users rather than directly from the company's servers.

(i) State what this network model is called.

.....[1]

(ii) Explain why the company might have opted for this model.

.....
.....
.....[2]

(b) InterMovie has a relational database of the films it offers. The database has the field *Film Title* which stores the name of a film (e.g. 'Aliens Attack').

(i) Describe why *Film Title* is not a suitable primary key.

.....
.....
.....[2]

(ii) Describe why *Film Title* would make a suitable secondary key.

.....
.....
.....[2]

3 The following assembly code in Fig.1 is written for the Little Man Computer instruction set.

```
      INP
      STA  arg1
      INP
      STA  arg2
      LDA  arg1
loop  SUB  arg2
      BRP  loop
      ADD  arg2
      OUT
arg1  DAT
arg2  DAT
```

Fig.1

(a) State the output when the inputs are 13 followed by 5.

.....[1]

(b) In the line:

```
loop  SUB  arg2
```

(i) State what opcode SUB does.

.....[1]

(ii) Name the register in which the result of this line is stored.

.....[1]

(c) (i) State what the program in Fig.1 does.

.....[1]

- (ii) Using pseudocode write a program for a procedural language that takes in two inputs and gives the same output as the program in Fig.1.

.....

.....

.....

.....[2]

4

- (a) Convert the denary number 43 into an 8 bit binary number.

.....

.....[1]

- (b) Using binary subtraction, calculate your answer to the following. You must show your working.

$$\begin{array}{r} 01001100 - \\ \underline{00110010} \end{array}$$

.....

.....

.....[2]

- (c) Using two's complement convert the denary number -43 into an 8 bit binary number. You must show your working.

.....

.....

.....[2]

- (d) (i) Using normalised floating point binary representation using 4 bits for the mantissa and 4 for the exponent, represent the denary value 1.75. You must show your working.

.....

.....

.....[2]

- (d) (ii) Using normalised floating point binary representation using 4 bits for the mantissa and 4 for the exponent, represent the denary value **-1.75**. You must show your working.

.....
.....
..... [2]

5 Burger House is a fast food restaurant which wants to encourage healthy eating amongst its younger diners.

(a) (i) Shown below in Fig.2 is the Burger House children’s menu.

<u>Children’s Menu</u>
<u>Burgers</u>
Cheeseburger
Grilled chicken burger (<i>Healthy Option</i>)

<u>Side Dishes</u>
French fries
Salad (<i>Healthy Option</i>)
Carrot Sticks (<i>Healthy Option</i>)

<u>Desserts</u>
Chocolate Brownie
Fruit Salad (<i>Healthy Option</i>)

Fig.2

Children receive a free toy when they select a meal (i.e. one burger, one side dish and one dessert) made up of only healthy options.

- Let g be a Boolean value for if a child has chosen a *grilled chicken burger*.
- Let s be a Boolean value for if a child has chosen *salad*.
- Let c be a Boolean value for if a child has chosen *carrot sticks*.
- Let f be a Boolean value for if a child has chosen *fruit salad*.
- Let t be a Boolean value for whether a child receives a toy.

Write an expression using Boolean algebra to determine whether a child receives a toy when they select a meal.

$t =$

.....

.....[3]

(ii) Burger House wants to add this logic into its' till system.

Complete the code below assuming that g,s,c,f and t are Boolean variables with the same meaning as part (i).

```
t=false
if _____ then
    _____
endif
```

[2]

6 An electronics engineer needs a circuit with the following logic.

$$(A \wedge B) \vee (\neg A \wedge B) \vee (\neg C \wedge \neg D)$$

Complete and use the Karnaugh map below to simplify the expression above.

		AB			
		00	01	11	10
CD	00				
	01				
	11				
	10				

Simplified expression:

.....

.....[4]

BLANK PAGE

BLANK PAGE

BLANK PAGE

Copyright Information:

OCR is committed to seeking permission to reproduce all third-party content that it uses in the assessment materials. OCR has attempted to identify and contact all copyright holders whose work is used in this paper. To avoid the issue of disclosure of answer-related information to candidates, all copyright acknowledgements are reproduced in the OCR Copyright Acknowledgements booklet. This is produced for each series of examinations and is freely available to download from our public website (www.ocr.org.uk) after the live examination series.

If OCR has unwittingly failed to correctly acknowledge or clear any third-party content in this assessment material, OCR will be happy to correct its mistake at the earliest possible opportunity.

For queries or further information please contact the Copyright Team, First Floor, 9 Hills Road, Cambridge CB2 1GE.

OCR is part of the Cambridge Assessment Group; Cambridge Assessment is the brand name of University of Cambridge Local Examinations